

Pneumatics

# PNEUMATICS COURSE FOR VOCATIONAL TRAINING

*Work book*

A text book from



*Pneumatics*

# **PNEUMATICS COURSE FOR VOCATIONAL TRAINING**

*Work book*

*A text book from*

 **FESTO**  
DIDACTIC

1st-edition

© Copyright by FESTO DIDACTIC D-7300 Esslingen 1978

All rights reserved.

Printed in W. Germany

Reviser: Rolf Gänger

ISBN 3-8127-0051-4

## **Preface**

This book is part of the comprehensive educational training documentation of the Federal German Institute for Vocational Training Research (BBF) in the Federal German Institute for Vocational Training (BIBB) of the Federal Republic of Germany.

It is the task of the Institute to promote inter alia educational technologies. In this connection the teaching equipment as proven in many years of service is further developed with regard to contents and methods employed, and new teaching equipment is designed and issued. Using large-scale experimental models, multimedia systems have been and are being developed and tested. The media which originate in this way allow optimum training results to be obtained. They permit the application of various teaching methods and a variable use of hardware. Thus it is possible to work with this material both in specialist theory and in specialist practice.

The self-governing body of the BIBB is composed of representatives of the Federal German and "Land" ministries, and of employers' and employees' representatives. All interests are thus protected and optimum working conditions for research, development and production are guaranteed.

FESTO DIDACTIC has gained the licencing rights for foreign language editions and for sales outside the Federal Republic of Germany. Thus, it is to be possible to support vocational education in all areas where the experiences gained over a century in systematic vocational training have hitherto never been compiled so comprehensively nor in such a well-tested way.



## Index

	page
Test questions — physical principles	7
2. Exercise 1	9
Test questions to Exercise 1 — single-acting cylinder, 3/2-way valve, normally closed	11
3. Exercise 2	13
Test questions to Exercise 2 — service unit	15
4. Exercise 3	17
Test questions to Exercise 3 — 3/2-way valve, normally open	19
5. Exercise 4	21
Test questions to Exercise 4 — 3/2-way valve, piloted	23
6. Exercise 5	25
Test questions to Exercise 5 — one-way flow control valve	27
7. Exercise 6	29
Test questions to Exercise 6 — quick exhaust valve, silencer	31
8. Exercise 7	33
Test questions to Exercise 7 — shuttle valve	35
9. Exercise 8	37
Test questions to Exercise 8 — two-pressure valve	39
10. Exercise 9	41
Test questions to Exercise 9 — double-acting cylinder, piloted 4/2-way valve, 5/2-way valve	43
11. Exercise 10	45
Test questions to Exercise 10 — supply air throttling, exhaust air throttling	47
12. Exercise 11	49
Test questions to Exercise 11 — 4/2-way valve and 5/2-way valve, types of valve control-symbols, design of a circuit diagram	51
13. Exercise 12	53
Test questions to Exercise 12 — 3/2-way valve with adjustable control pressure triggering	55
14. Exercise 13	57
Test questions to Exercise 13 — relieving pressure regulator (pressure reducing valve)	59
15. Exercise 14	61
Test questions to Exercise 14 — time delay valve	63
16. Exercise 15	65
Test questions to Exercise 15 — displacement-step diagram	67
17. Exercise 16	69
Test questions to Exercise 16 — bending tool	71
18. Exercise 17	73
Test questions to Exercise 17 — bending tool	75



## Index

	page
Test questions — physical principles	7
2. Exercise 1	9
Test questions to Exercise 1 — single-acting cylinder, 3/2-way valve, normally closed	11
3. Exercise 2	13
Test questions to Exercise 2 — service unit	15
4. Exercise 3	17
Test questions to Exercise 3 — 3/2-way valve, normally open	19
5. Exercise 4	21
Test questions to Exercise 4 — 3/2-way valve, piloted	23
6. Exercise 5	25
Test questions to Exercise 5 — one-way flow control valve	27
7. Exercise 6	29
Test questions to Exercise 6 — quick exhaust valve, silencer	31
8. Exercise 7	33
Test questions to Exercise 7 — shuttle valve	35
9. Exercise 8	37
Test questions to Exercise 8 — two-pressure valve	39
10. Exercise 9	41
Test questions to Exercise 9 — double-acting cylinder, piloted 4/2-way valve, 5/2-way valve	43
11. Exercise 10	45
Test questions to Exercise 10 — supply air throttling, exhaust air throttling	47
12. Exercise 11	49
Test questions to Exercise 11 — 4/2-way valve and 5/2-way valve, types of valve control-symbols, design of a circuit diagram	51
13. Exercise 12	53
Test questions to Exercise 12 — 3/2-way valve with adjustable control pressure triggering	55
14. Exercise 13	57
Test questions to Exercise 13 — relieving pressure regulator (pressure reducing valve)	59
15. Exercise 14	61
Test questions to Exercise 14 — time delay valve	63
16. Exercise 15	65
Test questions to Exercise 15 — displacement-step diagram	67
17. Exercise 16	69
Test questions to Exercise 16 — bending tool	71
18. Exercise 17	73
Test questions to Exercise 17 — bending tool	75





## Test Questions

### Physical Principles

Name: \_\_\_\_\_

Date: \_\_\_\_\_

1. Write down the four most important physical quantities and the associated units.

..... in .....

..... in .....

..... in .....

..... in .....

2. What is the unit of force called in the SI system and what is the associated unit symbol?

The unit of force in the SI system is called .....

The unit symbol is .....

3. What is the formula for pressure  $p$ ? Use the standardized expressions.

$p =$  .....

4. The unit of pressure  $10 \frac{\text{N}}{\text{cm}^2}$  has a specific name.

$10 \frac{\text{N}}{\text{cm}^2} = 1$  .....

5. Convert the following:

1.013 bar = ..... kPa (psi)

980 mbar = ..... Pa (psi)

0.4 bar = ..... Pa (psi)


1040 mbar = ..... MPa (psi)

6. Select the correct statements applicable to absolute pressure.

- ☐ The air pressure given in the daily weather report is indicated as an absolute pressure.
- ☐ Absolute pressure is the pressure prevailing at the absolute zero pressure point.
- ☐ Absolute pressure is measured from the absolute zero pressure point.
- ☐ Absolute pressure is  $p_n = 101.3 \text{ kPa}$  (1.013 bar/14.688 psi).
- ☐ None of the above statements is exactly applicable.

7. Enter into the sketch the terms

- $p_e$
- fluctuating atmospheric pressure line
- $p_{abs}$
- absolute zero pressure



8. State the two gases which are the main constituents of air.

Air consists mainly of .....  
and .....

9. Complete the following sentence:

If air is heated in an open bottle, then .....

10. Complete the following sentence properly. It's a matter of pressure.

If a contained volume of air is heated, then .....

11. In a closed vessel of  $V_1 = 60 \text{ dm}^3$ , air is contained with a pressure  $p_{1abs} = 700 \text{ kPa}$  (7 bar/101.5 psi).

The temperature is  $T_1 = 280 \text{ K}$  ( $\approx 7^\circ \text{C}$ ). The temperature rises to  $T_2 = 300 \text{ K}$  ( $\approx 27^\circ \text{C}$ ).

What is the new pressure in the same vessel?

$$\frac{p_{1abs} \times V_1}{T_1} = \frac{p_{2abs} \times V_2}{T_2}$$

12 Select the correct statement concerning the standard condition of gases. Several statements are correct.

- ☐ The standard condition of gases refers to a pressure defined by DIN Standards and a defined temperature.
- ☐ The standard condition is defined in DIN 1343.
- ☐ Standard condition means normal condition. The usual state of gases at 20° C.
- ☐ Standard condition means  $p_n = 101.3 \text{ kPa}$  (1.013 bar/14.688 ps) and  $T_n = 273.15 \text{ K}$


13 Complete the following sentence to give a correct statement

If a gas which is under pressure is expanded, then

14. Select the statement which best describes how condensed water occurs

- ☐ Condensed water occurs as a result of the moisture in the air forming drops.
- ☐ Condensed water occurs when air saturated with water vapour is cooled down
- ☐ Condensed water occurs by cooling down saturated air

15 Complete the sketch such that the levels of the two liquid columns correspond to the physically correct condition.




16 Enter in the sketch the position at which the velocity of flow is a maximum



## 2. Exercise 1

### Problem

Machined components are to be ejected from a machine. Solve the problem with the equipment provided. Inform yourself first of all, however, from the next few pages about the construction, the function and the purpose of the devices used.




### Procedure

- 1 Prepare the equipment
- 2 Insert the single-acting cylinder
- 3 Insert the 3/2-way valve and the other elements
- 4 Connect the pneumatic devices with tubing
- 5 Establish the compressed air connection
- 6 Operate the 3/2-way valve
- 7 Dismantle, tidy up

Compressed air supply connection P  
Working line A  
Exhaust R

The number given on the plug-in board corresponds to the equipment.

The connecting tubes may not have any kinks. When using side valves (Chap. 2.6) with quick-sealing couplings, the exhaust port R must be opened by means of an inserted tube or a silencer. The manifold and the necessary quick couplings [4] will not be listed again in the following exercises.



### Equipment

- 1 Plug-in board
- 2 Tool (knife or scissors) connecting tubing with threaded connectors
- 3 Pressure connection point and connecting line
- 4 Quick coupling and manifold
- 5 Single-acting cylinder
- 6 3/2-way valve, normally closed
- 7 Pressure gauge

### Safety

Securely plug in pneumatic devices. Keep piston rod travel free. All threaded connectors must be checked before connecting the compressed air, because connecting tubes which become disconnected when compressed air is applied can lead to accidents. When uncoupling the quick coupling, the end piece of the connecting tube on connections to which compressed air is applied must be held firmly. Accident risk!



## Test Questions to Exercise 1

### Single-Acting Cylinder 3/2-Way Valve, Normally Closed

Name: \_\_\_\_\_


Date: \_\_\_\_\_

1 The direction of motion of pneumatic cylinders is

is

2 Draw the symbol of a single-acting cylinder

3 Put in the missing designations.



© by FESTO DIDACTIC

1

2

3

4

6

8

7

8

9

4. Give three examples of application for single-acting cylinders.


5. Why is the stroke length of a single-acting cylinder limited? Select the correct statement. The stroke length of a single-acting cylinder is limited because

- ☐ pressure is applied to only one side of the piston
- ☐ the opposing force of the compression spring is high
- ☐ the compressed spring takes up a lot of space
- ☐ none of the above statements is correct.

6. Why does the piston rod chamber require a vent? Select the correct answers. The piston rod chamber requires a vent


- ☐ to avoid an air cushion from occurring
- ☐ because air must flow around it for cooling
- ☐ to allow the displaced air to escape
- ☐ none of these answers is correct

7. What are the valves called that are represented by the following symbols:



Number of ports

Number of control positions



Number of ports

Number of control positions



Number of ports

Number of control positions



Number of ports

Number of control positions ...

8 What do the capital letters on valves signify?

A, B

P


R, S

9 The drawing shows a 3/2-way valve. In which position is the valve?

☐ Normal position

☐ Mid position

☐ Open position



10 What is the symbol for the valve shown alongside? Complete the symbol.





11 Give some examples of application for 3/2-way valves.

### 3. Exercise 2

#### Problem

A service unit is to be set properly for a control. You should however first of all inform yourself from the following pages about the construction, the function and the purpose of a service unit.



© by FESTO DIDACTIC

#### Procedure

- 1 Prepare the equipment
- 2 Mount the components
- 3 Connect properly
- 4 Set the regulator to operating pressure
- 5 Set the lubricator
- 6 Check the oil flow ahead of the vent hole on the 3/2-way valve by operating ( $\approx 50$  times)
- 7 Dismantle, tidy up

#### Notes

The plug-in board, the tool and the connecting tubes will be required in all other exercises. These items will not be specified particularly from this point onwards.

The correct setting of the lubricator can be checked as follows:

A white piece of paper is held 5 cm away from the exhaust port R.

After operating the valve about 50 times, one should be able to see a fine oil stain on the paper. The valve silencer must be removed for this.

#### Equipment

- |   |  |
|---|--|
| 1 | Single-acting cylinder   |
| 2 | 3/2-way valve, normally closed ( $\overline{C}/\overline{W}$ ) |
| 3 | Pressure gauge   |
| 4 | 3/2-way valve for on-off (energy supply)                       |
| 5 | Service unit   |

#### Safety

Do not exceed the maximum pressure range of the service unit.





## Test Questions to Exercise 2

### Service Unit

Name: \_\_\_\_\_

Date: \_\_\_\_\_

© by FESTO DIDACTIC



- 1 You are given the following devices: filter, filter with water trap, pressure regulator, pressure gauge, lubricator. Allocate these to the respective functions given below. Note that some functions are listed which do not correspond to the devices given above.
  - Hold pressure constant
  - Clean air
  - Reduce pressure to preset value
  - Moisten air
  - Provide pressure indication
  - Enrich air with oil mist
  - Shut off pressure
  - Measure air flow
  - Filter air and remove condensate
- 2 Draw the simplified symbol for a service unit.
- 3 What is the purpose of the lubricator?
  - ☐ to clean the air by means of an oil mist
  - ☐ to combine water with oil in order to extract water from the air
  - ☐ to enrich the air with an oil mist in order to lubricate the moving parts
  - ☐ to trap particles of dirt by the oil mist and collect them in the bowl of the lubricator
- 4 In which sequence is air handled in a service unit?
  - Label the sequence by the numbers 1, 2, 3.
  - Reduce pressure to a constant preset value
  - Clean the air of dust and dirt and remove water
  - Enrich the air with an oil mist
- 5 What is the most obvious difference in appearance between filter and lubricator?
  - ☐ the size
  - ☐ the drip dome (sight glass) on the lubricator
  - ☐ water collects at the bottom of the filter
  - ☐ oil can be seen as the visible liquid in the lubricator
- 6 What does the symbol for a lubricator look like?
- 7 Draw the symbol for a pressure gauge
- 8 Which component part of the pressure gauge converts the pressure to be measured to a movement?
  - ☐ Tube spring
  - ☐ Lever
  - ☐ Pointer
  - ☐ Gear rack segment and pinion
- 9 Where should the service unit be arranged in the pneumatic system?
  - ☐ immediately in front of each working element
  - ☐ immediately after the air compressor
  - ☐ immediately in front of each pneumatic system

.

## 4. Exercise 3

### Problem

A slide is to release a tool opening on pushing a button, and close again immediately after releasing the button. Try to solve the problem with the equipment listed below. Inform yourself beforehand, however, about the normally open 3/2-way valve.



### Procedure

- 1 Prepare the equipment
- 2 Mount the single-acting cylinder on the plug-in board
- 3 Mount the 3/2-way valve on the plug-in board
- 4 Connect the pneumatic devices
- 5 Establish the compressed air supply
- 6 Operate the 3/2-way valve
- 7 Dismantle, tidy up

### Notes

The 3/2-way valve has the following ports:  
Compressed air supply port P  
Working line A  
Exhaust R

### Equipment

- 1 Single-acting cylinder
- 2 3/2-way valve, normally open
- 3 Pressure gauge

### Safety

Plug in pneumatic devices securely

Keep piston rod travel free.

All threaded connectors must be rechecked before establishing the compressed air supply because connecting tubes which disconnect due to the compressed air can cause accidents

When detaching the quick coupling, the end piece of the connecting tube in connections under pressure must be held firmly because of the danger of recoil.



## Test Questions to Exercise 3


### 3/2-Way Valve, Normally Open

Name: \_\_\_\_\_

Date: \_\_\_\_\_

- 1 Arrange the following subfunctions such that they result in the function of a normally open 3/2-way valve (poppet valve). Be quite clear first about the working sequence without paying any attention to the subfunctions. Then write them down line by line.

Valve disc is moved against spring [6] / plunger is pressed / supply flow from P is interrupted / A to R is open / part [2] is moved against spring [5] / shouldered pin contacts valve disc [3] / valve disc [4] closes bore [7]




© by FESTO DIDACTIC

- 4 What changes are necessary to make a normally open 3/2-way valve from a normally closed 3/2-way valve (slide valve type)?

- 5 Tick off the reason why the normally closed 3/2-way valve (poppet valve type) shown here cannot be converted to a normally open valve by interchanging ports P and R.

- ☐ Bore [1] missing in housing  
☐ Valve disc spring [2] is too weak  
☐ Plunger spring [3] is too strong, valve disc lifts off  
☐ Opening of the valve seat [4] by air pressure



- 2 Draw the symbol for a normally open 3/2-way valve

3. Give an example of application for a normally open 3/2-way valve










### 3/2-Way Valve, Piloted

**Date:** \_\_\_\_\_

- ® by FESTO DIDACTIC






## 6. Exercise 5

### Problem

The single-acting cylinder is to travel out slowly in order to avoid damaging the plastic pin which is to be pressed in. The outward stroke speed of the cylinder is to be adjustable. Solve the problem using the specified equipment and procedure. But first inform yourself from the next few pages about the construction and the principle of operation of a one-way flow control valve.



© BY FESTO DIDACTIC

### Procedure


1. Prepare the equipment
2. Mount the parts
3. Connect properly
4. Check the function of the cylinder and directional control valve by operating the directional control valve
5. Turn the regulating screw on the one-way flow control valve
6. Check whether the outward stroke speed can be controlled
7. Set various piston rod speeds
8. Dismantle, tidy up

### Notes

The outward stroke speed of the piston must be adjustable. It is therefore necessary to ensure that the one-way flow control valve is connected properly (direction of arrow = throttling direction).

Tighten each locknut after setting the regulating screw

Never tighten the regulating screw with force (damage to the valve), and also never unscrew it completely when working pressure is applied. Otherwise it will fly out. Accident risk!



### Equipment

1. Single-acting cylinder
2. One-way flow control valve
3. Normally closed 3/2-way valve (Q=1/4" NPT)
4. 2 pressure gauges

### Safety

Keep the piston traverse free. Mount devices securely

Before connecting the compressed air supply, all threaded connections should be checked because connecting tubes which disconnect under compressed air can cause accidents.

When uncoupling the quick coupling, the end piece of the connecting tube with connections under pressure must be held tight because of the recoil risk

Do not completely unscrew the regulating screw (see notes)



## Test Questions to Exercise 5

### One-Way Flow Control Valve

Name: \_\_\_\_\_

Date: \_\_\_\_\_

- 1 From which two devices is a one-way flow control valve built?

a)


b)

- 2 Draw the symbols for the devices from which the one-way flow control valve is built

- 3 Draw the symbol for a variable one-way flow control valve.




- 4 Complete the drawing of a spring-loaded check valve



- 5 Complete the drawing of the variable flow control valve



- 6 Complete the drawing of the variable one-way flow control valve






## 7. Exercise 6

### Problem

The single-acting cylinder is to return to its initial position very quickly after the pin has been pressed in. To accomplish this, the cylinder must be linked to a quick exhaust valve such that the piston side is exhausted as quickly as possible. To reduce the exhaust noise from the quick exhaust valve, a silencer is to be used.




### Procedure

1. Prepare the equipment
2. Mount the parts and connect properly
3. Check the function by operating the valve
4. Set the flow control valve such that the piston rod has travelled out to its full extent in 1 to 2 seconds
5. Compare the time of the outward and return strokes by measurement. If necessary estimate the return time
6. Remove the silencer and check the difference in noise level when exhaust occurs
7. Remove the quick exhaust valve and compare the times for the outward and return strokes
8. Disassemble, tidy up

### Notes

The quick exhaust valve must be connected properly. Port A is connected with the cylinder. Port P is connected with the pressure source through a flow control valve and a 3/2-way valve.

Connect the quick exhaust valve with the cylinder by means of a double nipple or a very short piece of tubing.



### Equipment

1. Single-acting cylinder
2. Quick exhaust valve with silencer
3. Normally closed 3/2-way valve ( $Q=1/4W$ )
4. One-way flow control valve
5. Stop watch

### Safety

At stage no 6 in the procedure, the cylinder exhaust escapes to the atmosphere in a burst for this reason, it should not be directed towards the eyes. The sudden decompression of the air is accompanied by an explosive noise which can shock people.

When uncoupling the quick coupling, the end piece of the connecting tube with connectors subjected to pressure must be held tightly because of the recoil risk.






## Test Questions to Exercise 8

### Quick Exhaust Valve Silencer

Name: \_\_\_\_\_  
Date: \_\_\_\_\_

- 1 In the circuit diagram below, symbols of pneumatic devices are labelled with numbers. The standard names for these are to be entered in the table below.



© by FESTO DIDACTIC

- |   |
|---|
| 1 |
| 2 |
| 3 |
| 4 |
| 5 |

- 2 In the cross-sectional views of the quick exhaust valve shown below, the ports are to be labelled (numbers, directional arrows) and the position of the sealing ring is to be drawn in for the following conditions:

Fig ① way P → A open, outlet R closed





Fig ② way A → R open, air supply port P pressureless





- 3 What is the purpose of a quick exhaust valve?
- ☐ Quick exhaust of cylinders and tubes
  - ☐ Quick exhaust of compressors
  - ☐ In emergencies, the quick exhaust valve exhausts the entire pipeline system
- 4 Which is the correct description of the principle of operation of a silencer?
- ☐ The exhaust air entering the silencer is distributed over a large surface area. The speed of the air is reduced by its flowing past the sintered particles contained in labyrinth style in the damping material
  - ☐ The silencer throttles the exhaust air by the sintered particles which it contains. The exhaust noise is thus also reduced.
  - ☐ The exhaust air entering the silencer is retained by the plastic particles arranged in labyrinth style and therefore cannot release the exhaust noise to the outside



## 8. Exercise 7

### Problem

A single-acting cylinder is to be operated through a shuttle valve by two different 3/2-way valves.



### Procedure

- 1 Prepare the equipment
- 2 Mount the parts
- 3 Connect properly
- 4 Check the function of the circuit by alternately operating the two directional control valves
- 5 Check whether the piston travels out if both valves are operated at the same time
- 6 Dismantle tidy up

### Note

The shuttle valve is also designated as a logic OR. If a signal is present at X **or** Y, A gives an output signal.

### Equipment

- 1 Single-acting cylinder
- 2 Shuttle valve
- 3 Two 3/2-way valves, normally closed (C=WW)

### Safety

Connect the compressed air supply only after assembly has been completed.

Keep the piston rod travel free.

All threaded connectors are to be checked before connecting the compressed air supply because connecting tubes which disconnect under pressure can cause accidents.



## Test Questions to Exercise 7


Name: \_\_\_\_\_

### Shuttle Valve

Date: \_\_\_\_\_

1 Draw the symbol for a shuttle valve

5 Through which port in a shuttle valve does the exhaust air escape if supply air enters through Y and the weight of the ball acts against port X?



2 What is the intended purpose of the shuttle valve?

- ☐ It should allow reversal of the piston's direction of movement.
- ☐ It should allow alternate exhausting.
- ☐ It should allow a device to be operated from two different points.
- ☐ It should allow two pneumatic devices to be connected

The exhaust air escapes through \_\_\_\_\_ because \_\_\_\_\_

6 Why is the shuttle valve also called an OR valve?

© by FESTO DIDACTIC

3 Sketch a cross-sectional view of a shuttle valve



4 Complete the description of the principle of operation of a shuttle valve.



The shuttle valve allows compressed air to flow from the applicable port X or Y to \_\_\_\_\_. The ball is \_\_\_\_\_ by the air flowing in and \_\_\_\_\_ the opposite port.



## 9. Exercise 8

### Problem

A single-acting cylinder is to extend only when two 3/2-way valves are operated at the same time.



### Procedure

- 1 Prepare the equipment
- 2 Mount the parts
- 3 Connect properly
- 4 Check the function of the circuit by operating the two directional control valves at the same time
- 5 Check whether the piston extends when one of the valves is operated
- 6 Set the pressure reducing valve to  $p_e = 300 \text{ kPa}$  (3 bar/43.5 psi)
- 7 Loosen connecting tube from port A of the two-pressure valve
- 8 Operate the 3/2-way valve with both hands and observe the pressure gauges
- 9 Discuss your observations with the instructor
- 10 Dismantle, tidy up

### Notes

The two-pressure valve is also designated as a logic AND. Only when a signal is applied to X and Y does A give an output signal.

### Equipment

- 1 Single-acting cylinder
- 2 Two-pressure valve
- 3 2 normally closed 3/2-way valves ( $\phi = 1/4''$ )
- 4 2 pressure gauges

### Safety

Do not make the compressed air connections until assembly is completed.

Keep the piston rod travel free.

All threaded connectors are to be checked before connecting the compressed air since connecting tubes which recoil due to pressure may cause accidents.





## Test Questions to Exercise 8

Name: \_\_\_\_\_


### Two-Pressure Valve

Date: \_\_\_\_\_

1 Draw the symbol of a two-pressure valve.

- 2 What is the purpose of a two-pressure valve?
- ☐ It is to trigger the function of a device when actuating two buttons at the same time
  - ☐ Two pneumatic devices are to be supplied with pressure at the same time.
  - ☐ It is to enable the actuation of a device from two points at the same time
  - ☐ It is to enable operation with two pressures.
- 3 Sketch the cross-section of a two-pressure valve

© by FESTO DIDACTIC





- 4 Complete the description of the principle of operation of a two-pressure valve.
- First, compressed air flows from Y to the valve.
- The port , . . . . . is then supplied with air through the port . . . . .
5. Why is the two-pressure valve also called an AND valve?



## 10. Exercise 9

### Problem

A double-acting cylinder is to be connected with a 4/2-way valve such that the piston rod travels out after connecting the compressed air and operating the valve.



© by FESTO DIDACTIC



### Procedure

1. Prepare the equipment
2. Mount the parts
3. Connect properly
4. Check the function by operating the 4/2-way valve
5. Dismantle, tidy up

Check the working pressure.

If the piston rod travels out when the compressed air is connected, the connecting tubes have been attached incorrectly.

### Equipment

1. Double-acting cylinder
2. 4/2-way valve  or  
5/2-way valve 

### Safety

Plug in pneumatic devices securely

Keep piston rod travel free

Observe permissible pressure.



## Test Questions to Exercise 9

### Double-Acting Cylinder Piloted 4/2-Way Valve 5/2-Way Valve

Name: \_\_\_\_\_

Date: \_\_\_\_\_

1. The piston with piston rod, seals and bearing should be drawn into the drawing below of a double-acting cylinder



2. What advantages and disadvantages does the double-acting cylinder have compared with the single-acting cylinder?

Advantages: .....


Disadvantages:

3. Calculate the force when a double-acting cylinder travels out and in (ignoring friction). Piston diameter 32 mm, piston rod diameter 12 mm, at a supply pressure of 600 kPa (6 bar/ 87 psi). Use the back of the sheet for the calculation
4. What is the purpose of 4/2-way valves and 5/2-way valves?
- ☐ These directional control valves control single-acting cylinders (advance and return) and are used in production.
  - ☐ These directional control valves control the compressed air with small switching forces, especially with hydraulic drives.
  - ☐ These directional control valves control double-acting cylinders.
  - ☐ None of these statements correctly describes the purpose of pilot 4/2-way valves.


5. Describe the working principle of a pilot 4/2-way valve making use of the subfunctions below

Valve plungers **11** and **13** push down, valve seat sleeves **14** and **15** open  $P \rightarrow A$  and  $B \rightarrow R$

control stud is operated, valve disc **3** is pushed down ports  $P \rightarrow B$  and  $A \rightarrow R$  are closed, diaphragms **10** and **12** are subjected to compressed air



6. Complete the symbol for the 5/2-way valve.






## 11. Exercise 10

### Problem


A 4/2-way valve or 5/2-way valve and a one-way flow control valve are to be connected with a double-acting cylinder in accordance with the circuit diagrams shown below in such a way that the advance of the piston rod is throttled when the directional control valve is actuated.



### Procedure

- 1 Prepare the equipment
- 2 Mount the parts and properly connect the supply air throttling arrangement
- 3 Check the function of the circuit by operating the directional control valve
- 4 Set various piston speeds
- 5 Close off the compressed air supply
- 6 Connect properly the exhaust air throttling arrangement
- 7 Set various piston speeds
- 8 Dismantle, tidy up

The exercise consists of two parts. In the first part, the supply air is throttled, and in the second part the exhaust air. The different effects of the two controls can be seen on the pressure gauges during the piston stroke. Please also note on a sheet of paper the pressures  $p_{e1}$  and  $p_{e2}$  for each circuit during and after the outward stroke. The values will be required for the test.



### Equipment

- 1 Double-acting cylinder
- 2 4/2-way valve or 5/2-way valve
- 3 One-way flow control valve
- 4 2 pressure gauges

### Safety

Do not screw out the regulating screw on the one-way flow control valve too far.  
When converting the control from supply air to exhaust throttling, always disconnect the compressed air.  
When uncoupling the quick coupling, the end piece of the connecting tube of connections under pressure must be held firmly because of the recoil risk.





## Test Questions to Exercise 10

### Supply Air Throttling Exhaust Air Throttling

Name: \_\_\_\_\_

Date: \_\_\_\_\_

- 1 Draw in the correct position of the one-way flow control valve for supply air throttling



- 3 State the main feature of exhaust air throttling by completing the following sentence  
The pressures which you have measured should help you

Pressure on outward stroke

$p_{e1}$

$p_{e2}$

kPa (bar/ps.)

... kPa (bar/ps.)

on exhaust air throttling, the piston is


- 4 State an area of application for supply air throttling and exhaust air throttling.  
Supply air throttling is used mainly with a constant

acting against the direction of

Exhaust air throttling is used mainly where

© by FESTO DIDACTIC

- 2 Draw in the correct position of the one-way flow control valve for exhaust air throttling







## 12. Exercise 11

### Problem

A double-acting cylinder is to travel out after operating a pushbutton and, after having travelled out to the full extent, automatically travel in again



### Procedure

- 1 Prepare the equipment
- 2 Mount the parts
- 3 Connect properly
- 4 Check the function by operating the pushbutton of the 3/2-way valve
- 5 Dismantle, tidy up

### Equipment

- 1 Double-acting cylinder
- 2 4/2-way or 5/2-way valve (→↔←)
- 3 Normally closed 3/2-way valve (↔↔↔)
- 4 Normally closed 3/2-way valve (↔↔↔)

### Safety

Be careful when switching on the compressed air supply! The present control position of the valve cannot be identified from the outside. The piston rod can therefore also move out immediately after switching on the supply. This will be the case if the previous user has dismantled the control with the piston rod in the extended position. The devices should therefore be dismantled only when the piston rod is in the retracted position.

Note the working pressure:

$$p_e = 400 \text{ kPa} \quad 600 \text{ kPa} \quad (4 \text{ bar} \quad , \quad 6 \text{ bar} / 58 \text{ psi} \quad , \quad 87 \text{ psi})$$

Be careful also with the forward movement of the piston rod. It returns on its own.

All threaded connectors should be checked before connecting the compressed air supply because connecting tubes which become disconnected under pressure can cause accidents.



## Test Questions to Exercise 11

### 4/2-Way Valve and 5/2-Way Valve Types of Valve Control-Symbols Design of a Circuit Diagram

Name: \_\_\_\_\_


Date: \_\_\_\_\_

- 1 Here are 8 symbols and 8 names. Write the correct name beneath each symbol.

Pushbutton; lever; detent roller lever, roller lever with detent return; 5/2-way valve (impulse valve)



- 2 Draw in the paths of the compressed air in this control position. Use circles to mark the places on the moving parts which have to be sealed specially



3. What causes the spool in an impulse valve to be moved

- ☐ The compressed air flowing in through P reverses the position of the spool
- ☐ The spool is reversed by the vacuum which arises.
- ☐ The pressure signal produced by the 4/2-way valve reverses the spool
- ☐ The spool is reversed by the force which results from applying compressed air to one of the spool chambers.

- 4 In which sequence should the devices in a circuit diagram be arranged?



- 5 Draw a circuit diagram for the following function


After the compressed air supply has been switched on, a double-acting cylinder is to travel in and out continuously  
Use the back of the sheet



### 13. Exercise 12



### Problem

A workpiece is to be fed to a fixture via a magazine and be clamped by a cylinder. After the first cylinder has clamped firmly, a second cylinder is to stamp the component.



**by FESTO DIDACTIC**




## Procedure

- 1 Prepare the equipment
- 2 Mount the parts and connect properly
- 3 Check the function by operating the 4/2-way valve or 5/2-way valve (  )  
Operate once briefly, and then for a longer period and observe the pressure gauge while doing so
4. Reset the spring on the pressure switching valve 
- 5 Operate and observe
6. Dismantle, tidy up

## Notes

From this exercise on, the plug-in board will no longer be shown. You can now arrange the devices yourself in accordance with the circuit diagram.

### Equipment

- 1 2 double-acting cylinders
- 2 Quick exhaust valve
- 3 One-way flow control valve
- 4 Pressure gauge
- 5 4/2-way valve or 5/2-way valve ()
- 6 4/2-way valve or 5/2-way valve ()
- 7 3/2-way valve with adjustable control pressure triggering ()

## Safety

**Note the working pressure**

$p_0 = 400 \text{ kPa} \dots 600 \text{ kPa}$  (4 bar ... 6 bar/  
58 psi ... 87 psi)

All connections must be checked before switching on the compressed air supply, because connecting tubes which become disconnected can cause accidents.

**The piston rod paths must be kept free**






## Test Questions to Exercise 12

### 3/2-Way Valve with Adjustable Control Pressure Triggering

Name: \_\_\_\_\_

Date: \_\_\_\_\_

- 1 Here is the symbol for a 3/2-way valve with adjustable control pressure triggering. Answer the following questions



- a) Is the valve open or closed in the normal position?

☐ open  
☐ closed

- b) What is the meaning of the triangle drawn in this form at outlet R?

- c) What is the meaning of the arrow through the spring?

The arrow


- 2 The diaphragm surface in a 3/2-way valve with adjustable control pressure triggering is  $12 \text{ cm}^2$ . The preset spring force is measured as 36 N. To which value must the control pressure rise in order for the valve to reverse? (Note: Pressure equals force divided by area.)

- 3 What is the function of the O-ring on the valve plunger [4]?

☐ It must seal the way to R when reversal takes place  
☐ It must seal the way to A before reversal takes place  
☐ It must seal P after reversal takes place.

4. Put in the correct order the functional sequence when the valve closes.

Spring [3] pushes ball [2] back on its seat. / Spring [6] pushes the actuating piston [5] back. / Thus, valve plunger [4] also returns under the action of the spring force [3]. / P is closed and exhaust is possible from A to R.






## 14. Exercise 13

### Problem

Plastic parts are to be stamped with a heated die. The stamping force should always be constant and adjustable within certain limits. You should solve this problem with a pressure regulator.



© by FESTO DIDACTIC

### Procedure

1. Prepare the equipment
2. Mount the parts and connect properly
3. Check the function by operating the 3/2-way valves
4. Set the pressure regulator to various values
5. Operate and observe the pressure gauge
6. Dismantle, tidy up

### Notes

The piston rod will always travel out when switching on the air supply if the previous user switched off the system while the rod was in the extended position and removed the 4/2-way valve or 5/2-way valve, or if the cylinder ports are interchanged. Apart from the quick exhaust function, the quick exhaust valve has the function in this exercise of not allowing the exhaust air to flow through the pressure regulator.

### Equipment

1. Double-acting cylinder
2. Quick exhaust valve
3. Pressure regulator with pressure gauge
4. 4/2-way valve or 5/2-way valve (—/—)
5. Two 3/2-way valves, normally closed (—/—)

### Safety

Note the working pressure:

$$p_a = 400 \text{ kPa} \dots 600 \text{ kPa} \quad (4 \text{ bar} \dots 6 \text{ bar} / 58 \text{ psi} \dots 87 \text{ psi})$$

When switching on the compressed air supply make sure that the piston rod can also travel out immediately because the control position of the 4/2-way or 5/2-way valve cannot be seen from the outside.

Keep the piston rod path free






## Test Questions to Exercise 13

### Relieving Pressure Regulator (Pressure Reducing Valve)

Name: \_\_\_\_\_

Date: \_\_\_\_\_

1. Which is the symbol for a relieving pressure regulator to ISO 1219? (Mark with a cross)



3. Name an example of application for a relieving pressure regulator

4. According to the manufacturer, 150 N are required for working the plastic parts. Unless you have found another value experimentally, add another 10 N for overcoming the friction of the cylinder. To which value must you set your pressure regulator?

Calculation of the cylinder surface area


Cylinder bore  $d =$  \_\_\_\_\_ cm

$$A = \frac{d^2 \times \pi}{4} \text{ in cm}^2$$

$A =$  \_\_\_\_\_

2. What happens if a pressure surge occurs on the secondary side (port A)?

- ☐ Valve plunger [5] opens against compression spring [7]
- ☐ Valve seat ring [4] and diaphragm lift the valve plunger [5] and thus allow flow to occur
- ☐ Spring [8] is compressed by the valve seat ring [4] and the diaphragm [3] thus allowing flow through the bore in [4]



Calculation of setting pressure


$p =$  \_\_\_\_\_



## 15. Exercise 14

### Problem

Plastic parts are to be fused together by heating while at the same time pressing them together. The fusing time is to be variable because various material thicknesses are processed.



© by FESTO DIDACTIC

### Procedure

- 1 Prepare the equipment
- 2 Build up in accordance with the circuit diagram and connect properly
- 3 Check the function by operating the 3/2-way valve
- 4 Adjust the dwell time on the time delay valve
- 5 Verify with the stop watch whether the dwell time is always the same at any one setting
- 6 Find out between which limits the dwell time can be varied
- 7 Dismantle, tidy up

### Equipment

- 1 Double-acting cylinder
- 2 One-way flow control valve
- 3 Pressure gauge
- 4 4/2-way valve or 5/2-way valve
- 5 Normally closed 3/2-way valve
- 6 Normally closed time-delay valve
- 7 Stop watch

### Safety

Note the working pressure:

$$p_e = 400 \text{ kPa} \quad 600 \text{ kPa} \quad (4 \text{ bar} \quad 6 \text{ bar} / 58 \text{ psi} \quad 87 \text{ psi})$$

Do not get in the way of the piston rod path  
Rectify faults only when the system is switched off, ON – OFF,






## Test Questions to Exercise 14

### Time Delay Valve

Name: \_\_\_\_\_

Date: \_\_\_\_\_

- 1 Which three devices make up a time delay valve?



- a) \_\_\_\_\_  
b) \_\_\_\_\_  
c) \_\_\_\_\_

- 2 What is the meaning of the thin dot-dash lined rectangle in the symbol of the time delay valve?


- ☐ Designation of the device  
☐ Timing elements are represented in this way symbolically  
☐ Designation of an assembly  
☐ The device is switched by a control line

- 3 Which operation allows the time-delayed switching of the time delay valve?

- ☐ The slow non-return action  
☐ The time-delayed throttling of the check valve  
☐ The slow build-up of pressure in the capacitor  
☐ The spring force of the 3/2-way valve

- 4 Name an example of application for a time delay valve

- 5 What is the function of the various devices in the circuit diagram? Continue the table.



No	Name	Function
1	Cylinder	Pressing
2	One-way flow control valve	Throttles exhaust from 1
3		
4		
5		
6		

9  
10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
8

1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
---	---	---	---	---	---	---	---	---	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	----	-----

[illegible]



三

## 17. Exercise 16

### Problem

Metal sheets are to be flanged on a pneumatically operated bending tool. After the part has been clamped, it is bent by a double-acting cylinder 1.0 and then the finish bend is effected by another double-acting cylinder 2.0. Triggering is by means of a manual pushbutton. The circuit should be designed such that each time a start signal is given one working cycle is performed.

### Positional sketch



### Procedure

1. Prepare the equipment
2. Build up in accordance with the circuit diagram
3. Check the function by means of 1.2
4. Convert the circuit for another tool. Cylinder 1.0 is to travel out quickly and travel in slowly. Fit in the return the flow control valve from the advance
5. Throttle more from working cycle to working cycle and observe the control
6. Discuss observations with the Instructor
7. Dismantle, tidy up

### Notes

The term signal switch-off is explained in Exercise 17

### Equipment

- 1 2 double-acting cylinders
- 2 2 one-way flow control valves
- 3 Two 4/2-way valves or 5/2-way valves
- 4 Normally closed 3/2-way valve (□=WV)
- 5 Normally closed 3/2-way valve (□=WV)
- 6 2 normally closed 3/2-way valves (□=WV)

### Safety

When searching for faults, never operate the roller levers by hand — danger of crushing!



## Test Questions to Exercise 16

### Bending Tool

Name: \_\_\_\_\_

Date: \_\_\_\_\_

- 1 Draw the symbol of a normally closed 3/2 way valve with idle return roller and spring return





3. Name a disadvantage of controls with idle return roller valves

- 2 What is the advantage of controls with idle return roller valves?

- 4 Design the circuit diagram for the following displacement-step diagram

© by FESTO DIDACTIC

Component		State	
Device No.	Name	Function	Pos.
1.0	Double-acting cylinder	Bending	Out In
1.1	5/2 way valve	Controls 1.0	a b
1.2	3/2 way valve	Controls 1.1	a b
1.3	3/2 way valve	Controls 1.1	a b






## 18. Exercise 17

### Problem


Meta sheets are to be flanged on a pneumatically operated bending tool. A first bend is to be made with one cylinder. When this has retracted, the part is completed by a second cylinder.

Idle return rollers may not be used in the circuit.

Positional sketch



© by FESTO DIDACTIC



### Procedure

1. Prepare the equipment
2. Build up according to the circuit diagram
3. Check the function by 1.2.
4. Dismantle, tidy up

### Equipment

1. 2 double-acting cylinders
2. Three 4/2-way valves or 5/2-way valves
3. Normally closed 3/2-way valve
4. 3 normally closed 3/2-way valves





## Test Questions to Exercise 17

### Bending Tool


Name: \_\_\_\_\_

Date: \_\_\_\_\_

1. Name two methods of signal switch-off.

- a) .....  
b) .....

2. Draw the displacement-step diagram for this exercise until all devices are in their initial positions.



© by FESTO DIDACTIC

Component				State	Step																		
Device No.	Name	Function	Pos.		0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
1.0	Double-acting cylinder	Bend	Out In				22		13					22									
2.0	Double-acting cylinder	Finish bend	Out In																				
1.1	4/2- or 5/2-way valve	Controls 1.0	a b																				
2.1	4/2- or 5/2-way valve	Controls 2.0	a b																				
1.2	3/2-way valve	START	a b																				
2.2	3/2-way valve	Controls 2.1	a b																				
0.2	4/2- or 5/2-way valve	Controls 1.1 2.1	a b																				
1.3	3/2-way valve	Controls 0.2	a b																				
2.3	3/2-way valve	Controls 0.2	a b																				



A pneumatics course has been developed by the BBF, assisted by FESTO DIDACTIC, for vocational basic training. The student is to implement experimentally the knowledge imparted in the text book in exercises using the training table and the BBF construction kit; he thus learns through play. The level of knowledge attained can be checked

at any time thanks to the tests given in the work book. In the manual for the instructor, further knowledge and examples are detailed.

**Contents:**

17 exercises  
Single-acting cylinder  
Double-acting cylinder  
3/2, 4/2 and 5/2 way valves  
Shutoff valves, pressure valves,  
flow control valves  
Diagrams  
Design of circuit diagrams  
Practice examples based on  
practical tasks.